# AERATRON

### **Aeratron 10Volt Automation Control Instruction**





**IMPORTANT** The 10Volt Automation control must be installed by a licensed and qualified electrician. Automation System components are not supplied by Aeratron **NOTE:** The Voltage control interface must operate at SELV (Safe Electrical Low Voltage) levels.


#### - Automation System (Voltage Controlled)


Fan motion and Light functions are controlled by applying positive DC voltage at the voltage control input VIN.
Blue = VIN control signal 0 to 10V,
White = 0V.

FUNCTION	CONTROL VOLTAGE VIN(Volts)		
IDLE (no operation)	0.5		
FAN STOP	1.3		
SPEED 1 (slowest)	2.1		
SPEED 2	2.9		
SPEED 3	3.7		
SPEED 5	4.5		
SPEED 6 (fastest)	5.3		
FORWARD	6.1		
REVERSE	6.9		
LIGHT ON (bright)	7.7		
LIGHT MEDIUM	8.5		
LIGHT OFF	9.3		









## **Aeratron 10Volt Automation Control Instruction**

#### **Operating conditions**

Operating conditions are shown below.

Parameter	Min	Тур	Max
Input impendance (VIN to 0V)		~17kΩ	
Input voltage (VIN)	0V		10V
Time to hold voltage at VIN	1s		
Time to change voltage VIN1> VIN2			200ms

- 1. A control operation is activated by applying DC voltage to VIN, according to Table 1 values, for a minimum period of 1s (Table 2).
- 2. After applying control voltage to VIN, the controlling interface can remain at the same voltage, or return to IDLE. When IDLE is selected, no operation will take place.
- 3. To changing rotational direction, set VIN to FORWARD or REVERSE as desired. The fan will change direction, and resume rotating at the same speed as before.
- 4. Fan control and Light control are separate operations. Turning Light ON or OFF does not affect fan motion. Changing fan setting does not affect the light setting.

For General Information & Warranty issues refer to the Aeratron™ User Manual available at www.aeratron.io

Thank you. Your Aeratron team.



Automation Control Edition 2021/08